



VX 200/4H S

PORTABLE POWER

Welding Sets Range WELDARC INTENS

PRODUCT ADVANTAGES

- HONDA Professional Engine
- Entire group guaranteed 3 years
- Light storage box integrated
- Solid and high-performance equipment
- Auxiliary Single phase output

Range WELDARC INTENS

Welding sets which can be used on sites where there is no electricity.



VX 200/4H S

WELDING SET SPECIFICATIONS

Range	WELDARC INTENS
Frequency (Hz)	50
Max power LTP (kW) *	4
Max power LTP (kVA)	4
Normal duty cycle 35% (A)	200
Intensif duty cycle 70% (A)	170
Stricking volts (V)	75
Rods diameter mini (mm)	1.6
Rods diameter maxi (mm)	4
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	103
Acoustic pressure level @1m in dB(A)	88
Acoustic pressure level @7m in dB(A)	74

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390
Distribution	O.H.V.
Start	Starter
Low Oil pressure shutdown	Oui
Displacement (cm3)	389
Oil capacity (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Lenght (cm)	87
Width (cm)	57
Height (cm)	55.50
Dry Weight (kg)	86

PACKAGING

Packaging type	Box / Pallet
Length (cm)	88
Width (cm)	58.50
Height (cm)	70
Weight (kg)	99
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



ACCESSORIES SUPPLIED



Storage box



User and maintenance manual

OPTIONS



R01

R01

This set includes the hour meter and the differential circuit breaker.



R07

R07

Trolley kit for generating sets > 3 kW with a stretcher system for easy handling.



R10

R10

Welding kit includes 2 x 5 m of cable, 1 earth clip, 1 electrode holder, 1 hammer, 1 brush and 1 mask.



RBH1

RBH1

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5

RBH0-5

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RH2

RH2

Cover for SDMO 's generating sets, welding sets and water pumps



RPQ

RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.